

PAP2 Fax Setup

Line 1

change dialtone to:

400@-19,425@-19,450@-19;10(*0/1+2+3)

Audio Configuration	
Preferred Codec:	G711a ▼
Use Pref Codec Only:	no ▼
G729a Enable:	yes ▼
G723 Enable:	yes ▼
G726-16 Enable:	yes ▼
G726-24 Enable:	yes ▼
G726-32 Enable:	yes ▼
G726-40 Enable:	yes ▼
DTMF Process INFO:	yes ▼
DTMF Process AVT:	yes ▼
DTMF Tx Method:	Auto ▼
FAX Process NSE:	yes ▼
FAX Disable ECAN:	no ▼
Silence Supp Enable:	no ▼
Silence Threshold:	medium ▼
Echo Canc Enable:	no ▼
Echo Canc Adapt Enable:	no ▼
Echo Supp Enable:	no ▼
FAX CED Detect Enable:	yes ▼
FAX CNG Detect Enable:	yes ▼
FAX Passthru Codec:	G711a ▼
FAX Codec Symmetric:	yes ▼
FAX Passthru Method:	NSE ▼
DTMF Tx Mode:	Strict ▼
Hook Flash Tx Method:	None ▼
Release Unused Codec:	no ▼

FXS Port Polarity Configuration	
Idle Polarity:	Forward ▼
Caller Conn Polarity:	Reverse ▼
Callee Conn Polarity:	Forward ▼

Regional

Ring and Call Waiting Tone Spec	
Ring Waveform:	Sinusoid ▼
Ring Voltage:	85
Synchronized Ring:	no ▼
Ring Frequency:	20
CWT Frequency:	425@-20

Miscellaneous	
Set Local Date (mm/dd):	
Time Zone:	GMT+10:00 ▼
Daylight Saving Time Rule:	start=4/-1/7;end=10/1/7;save=1
FXS Port Input Gain:	-3
DTMF Playback Level:	-16
Detect ABCD:	yes ▼
Caller ID Method:	ETSI FSK With PR(UK) ▼
Caller ID FSK Standard:	v.23 ▼
More Echo Suppression:	no ▼
Set Local Time (HH/mm):	
FXS Port Impedance:	600 ▼
FXS Port Output Gain:	-3
DTMF Playback Length:	.1
Playback ABCD:	yes ▼
FXS Port Power Limit:	3 ▼
Feature Invocation Method:	Default ▼